



Dimensions with NEMA Motors - 60 Hz

Model	07.11		07.14			11.15			11.23		17.25	03.35
Motor Size	56	145	143	145	182	145	182	184	182	184	184	184
a1	2-21/32		2-21/32			2-21/32			2-21/32		2-21/32	2-21/32
L	14-15/16	16-15/16	15-15/16	16-15/16	18-1/2	16-15/16	18-1/2	19-1/2	18-1/2	19-1/2	19-1/2	19-1/2
Q	2-15/16		2-15/16			2-15/16			2-15/16		2-15/16	2-15/16
h1	3-1/2		3-1/2		4-1/2	3-1/2		4-1/2		4-1/2	4-1/2	4-1/2
h2	5-1/8		5-1/8			5-1/8			5-1/8		5-1/8	5-1/8
r	8-7/16	8-1/8	8-1/8		9-3/8	8-1/8	9-3/8		9-3/8		9-5/8	9-5/8
r1	5-7/8		5-7/8		6-5/8	5-7/8		6-5/8		6-5/8	6-5/8	6-5/8
rb	6-11/32		6-11/32		7-1/8	6-11/32		7-1/8		7-1/8	7-1/8	7-1/8
m1	3	5	4	5	4-1/2	5	4-1/2	5-1/2	4-1/2	5-1/2	5-1/2	5-1/2
n1	4-7/8	5-1/2	5-1/2		7-1/2	5-1/2		7-1/2		7-1/2	7-1/2	7-1/2
s1	3/8		3/8		13/32	3/8		13/32		13/32	13/32	13/32
g	5-7/16	5-29/32	5-29/32		7-1/32	5-29/32		7-1/32		7-1/32	7-1/32	7-1/32
L3	7-9/32		7-9/32		8-1/16	7-9/32		8-1/16		8-1/16	8-1/16	8-1/16
B2	9-3/4		9-3/4		12	9-3/4		12		12	12	12
S2	9/16		9/16			9/16			9/16		9/16	9/16
L1	9-21/32		9-21/32		10-3/16	9-21/32		10-3/16		10-3/16	10-3/16	10-3/16
B3	12-1/8		12-1/8		14-1/8	12-1/8		14-1/8		14-1/8	14-1/8	14-1/8
h3	1-9/16		1-9/16			1-9/16			1-9/16		1-9/16	1-9/16
DeM	1-1/4 MNPT											
DeA	1-1/2 MNPT											
KM (ISO) (*)	3-15/16		3-15/16			3-15/16			3-15/16		3-15/16	3-15/16
KA (ISO)	4-11/32		4-11/32			4-11/32			4-11/32		4-11/32	4-11/32
KM (ANSI) (*)	3-1/2		3-1/2			3-1/2			3-1/2		3-1/2	3-1/2
KA (ANSI)	3-7/8		3-7/8			3-7/8			3-7/8		3-7/8	3-7/8
KM (JIS) (*)	3-15/16		3-15/16			3-15/16			3-15/16		3-15/16	3-15/16
KA (JIS)	4-1/8		4-1/8			4-1/8			4-1/8		4-1/8	4-1/8
d x z (ISO)	3/4 x 4		3/4 x 4			3/4 x 4			3/4 x 4		3/4 x 4	3/4 x 4
d x z (ANSI)	5/8 x 4		5/8 x 4			5/8 x 4			5/8 x 4		5/8 x 4	5/8 x 4
d x z (JIS)	3/4 x 4		3/4 x 4			3/4 x 4			3/4 x 4		3/4 x 4	3/4 x 4

Dimensions in inches - Some dimensions may depend on motor size, please contact your rep for details.